



the loaded conditional command, to the computer. The memory, to which the microcontroller has access, may be particularly a register which is present on the microcontroller.

Due to its mode of operation, the microcontroller according to the invention allows a considerably greater flexibility in its use and in programming without extensive changes in the structure of the hardware being necessary. A conditional command can be used for programming in the same way as conventional assembler commands. When executing the program code, it ensures a greater flexibility because the actually performed instruction depends on the data which are present at the instant of forming this instruction in the memory to which the command decoder has access.

The memory, to which the command decoder has access, is preferably adapted in such a way that it can comprise input data of the microcontroller. Input data of the microcontroller may be particularly digital or digitized information supplied by a connected apparatus.

In accordance with a special embodiment of the invention, the command decoder is adapted in such a way that, dependent on the contents of the memory to which the command decoder has access, the conditional command is decoded as an access command for the computer to different memory types. The access to different memory types, starting from the same conditional command, is a frequently occurring situation of use in which the embodiment of the microcontroller according to the invention is particularly advantageous. Numerous microcontrollers have different assembler commands for access to different memories. For example, the microcontroller 80C51 has the command "mov" for moving data memory data and the command "movc" for code memory data. A generic pointer (for example in the high-level language C) which has address-controlled access to the overall implemented memory is possible for such microcontrollers with either considerable assembler code effort or with additional hardware-supported memory configurations (memory mapping). In contrast, the implementation of a data-controlled, conditional command with a single program command allows access to all implemented data memories, because the relevant desired instruction is decoded in dependence upon the data, for example, dependent on the contents of a processor register as a pointer. This operation has the external effect of access to a linear memory. It is therefore a great advantage that, for example, memory management units which are provided can be used without any change in spite of virtual reconfiguration of the memory.

The sole Figure diagrammatically shows the elements of a microcontroller 100 according to the invention.

5           The Figure only shows the arithmetic-logic unit ALU 12 and the command decoder 15 as logic components of the microcontroller 100 shown in a very simplified form. The ALU 12 and the command decoder 15 are connected to a common bus 13 to which the inputs 10 and outputs 11 of the microcontroller are also connected. The command decoder 15 further has a direct connection 16 with the ALU 12 via which the run-off control is  
10 performed.

          According to the invention, the command decoder 15 has direct access to a memory 14 which may be, for example, a register of the microcontroller. Data of different origin, for example, data from an input 10 of the microcontroller, may be loaded into the memory 14.

15           The command decoder 15 is adapted in such a way that it can perform conditional commands. In the case of a conditional command, the command decoder 15 selects one out of a plurality of associated machine commands in dependence upon the contents of the memory 14 and supplies this command to the ALU 12. For example, the command decoder may supply the command mov or the command movc to the ALU in  
20 dependence on the contents of the memory 14. However, in both cases, the starting point is the same conditional assembler command so that a distinction in this respect is not required during programming. The microcontroller according to the invention thus provides the possibility of considerably reducing the programming effort so that both the system performance and the code density can be significantly increased with a small number of  
25 additional hardware components.

Reference numerals:

100	microcontroller
10	input connection
11	output connection
30 12	computer
13	bus
14	memory
15	command decoder
16	connection